

AR321

Wireless Guitar System



KEY FEATURES



AFS(Automatic Frequency Selection)

Press the " ⏪ / ⏩ " button for 3 sec and the receiver will auto-scan and lock on to an open, interference free frequency.



IR Infrared Sync

Press [IR] button to pair automatically the receiver frequency with the transmitter.



Anti-Interference

PLL(Phase Lock Loop frequency control) design ensures transmission reliability, "NoiseLock" squelch effectively blocks stray RF.



Compatible systems

Maximum 24 set can be used simultaneously by using multiple frequency bands in one venue.



Full Band Transmitter

134MHz full band transmitter allows pairing with the receiver irrespective of frequency band.



Energy Conservation

Low RF power mode gives twice the battery life of up to 14 hours*.(On AA Alkaline Batteries)

AR2 BODYPACK TRANSMITTER



AR2 is a compact & lightweight body-pack style transmitter made for clip-on microphones housed in a durable metal body with a multifunction OLED display. The OLED display provides frequency, channel, lock & battery status. It comes to a mini XLR (TA4M input jack) terminal with an audio gain adjustment switch (0,-6,-12dB) and RF boost (10/40 mW) switch for a higher operating distance. With wide operating bandwidth of 134 MHz, it can be paired/synced with any of the Arche receivers irrespective of the frequency band of the receiver unit. The bodypack transmitter can be used with an AR-2H electret condenser headworn microphone with a omnidirectional capsule designed for speech & musical instruments.

CARRIER FREQUENCY RANGE	522MHz~936MHZ
OSCILLATION	PLL Synthesized
HARMONIC RADIATION	<45dBm
BANDWIDTH	134MHz(It depends on the region)
MAX. DEVIATION RANGE	±45KHz
INPUT CONNECTOR	TA4M/LEMO connector
RF OUTPUT POWER	10mW/40mW
BATTERY	AA x 2
CURRENT CONSUMPTION	110mA(Typical)
OPERATING HOURS	Approximately 14 hours*
DIMENSION (MM)	84(H) X66(W) X 23(D)
WEIGHT	155g (w/o battery)
HOUSING	Die cast metal body

*on 10mw RF

AR3 SINGLE CHANNEL DIVERSITY RECEIVER



AR3 is a 1/2 EIA standard Rack Unit metal chassis single-channel wireless receiver for AR1 & AR2 transmitters. Bright & intuitive LCD front panel display gives necessary information like RF level, Audio levels, working channel & transmitter battery status, etc. With 32MHz operating bandwidth, each receiver band allows up to 10 compatible systems which are interference-free. With multiple bands, it can reach up to 24 compatible systems*. The PLL synthesized circuitry ensures RF transmission reliability with separation from GSM & other EMI interference. AFS (Auto Frequency Selection) functions scan the environment and lock itself in an open interference-free frequency channel. The diversity antenna circuit chooses the better one receiving out of its 1/2 Wave Antennae to give optimum RF stability every time.

CARRIER FREQUENCY RANGE	522MHz~936MHz
MODULATION MODE	FM stereo modulation
OSCILLATION	PLL synthesized
SENSITIVITY	5dBμV, S/N>60dB at 25 deviation
OPERATING BANDWIDTH	32MHz (E,I,J,K)
MAX DEVIATION RANGE	±45KHz
S/N RATIO	>105dB
T.H.D	<0.7%@1KHz
FREQUENCY RESPONSE (AUDIO)	45Hz-18KHz ±3dB
OPERATING RANGE	100M typical*
POWER SUPPLY	DC 12V/12W adapter
DIMENSION (MM)	205(W)x206(D)x43(H)
WEIGHT	Approximately 1.0kg
OUTPUT CONNECTOR	XLR balanced & 6.3φ phone jack unbalanced
HOUSING	Pressed steel powder coated enclosure

*Actual range depends upon clear line of sight & interference

ERTHPOT ELECTRONICS PRIVATE LIMITED

A - 164, A Block, Noida Sector 63, Gautam Buddha Nagar
Uttar Pradesh Pin Code: 201301
info@erthpot.com